

QNF-8208 Transmitter specifications

Indicator	LCD 53x25 mm, with back light
Tone frequency	225 Hz
Max. distance of transmission	2 Km
Max. distance cable map	1 Km
Max. working current	Less than 70mA
Tone mode	2 Tone adjustable
Compatible connectors	RJ45
Max. signal voltage	15Vp-p
Function and faults LCD display	LCD display (wiremap, Tone, short, No adapter, Low battery)
Cable map indication	LCD (#1-#8)
Shielded indication	LCD (#9)
Voltage protection	AC 60V/DC 42V
Battery Type	DC9.0V (NEDA 1604/6F22 DC9V x 1pcs)
Dimension(LxWxD)	185x80x32mm

QNF-8208 Receiver specifications

Frequency	225kHz
The Max. working current	Less than 70mA
Earjack	1
LED illumination	2
Battery Type	DC9.0V (NEDA 1604/6F22 DC9V) x1pc
Dimension(LxWxD)	218x46x29 mm

QNF-8208 Remote unit specifications

Compatible connectors	RJ45
Dimension(LxWxD)	107x30x24mm