

Standard carton:

Carton size:48.8x43.5x44.5 cm

Quantity : 20pcs/ctn

Weight: 22kg

QNF-388 Transmitter specifications

Indicator	LCD 53x25 mm, with back light
Tone frequency	225 Hz
Max. distance of transmission	2 km
Max. distance of cable map	1 km
Max. working current	Less than 70mA
Tone mode	2 Tone adjustable
Compatible connectors	RJ11, RJ45, Coaxial, USB
Max. signal voltage	15Vp-p
Function selection	3 position buttons & 1 power switch
Function and faults LCD display	LCD display (wiremap, Tone, short, No adapter, Low battery)
Cable map indication	LCD (#1-#8)
Shielded indication	LCD (#9)
Voltage protection	AC 60V/DC 42V
Battery type	DC9.0V (NEDA 1604/6F22 DC9V) x 1pc
Dimensions (LxWxD)	185 x 80 x 32mm

QNF-388 Receiver specifications

Frequency	225kHz
The Max. working current	Less than 70mA
Earphone jack	1
LED illumination	2
Battery Type	DC9.0V (NEDA 1604/6F22 DC9V) x1pc
Dimension(LxWxD)	218x46x29 mm

QNF-388 Remote unit specifications

Compatible with connectors	RJ11, RJ45, Coaxial, USB
Remote units	8
Dimension(LxWxD)	107x30x24mm