

### QNF-868A Transmitter specifications

LCD screen	53x25mm
The Max. distance of tracing cable	2000 m
Max. distance of cablemapping	2000m
Max. distance of cable length testing	1000 m
Trace cable coonected to switch	Anti-jamming
Tone mode	2 Tones, adjustable
Compatible with connectors	RJ11,RJ45,BNC,USB
LED lights display	Wiremap, tone, tracing
Cable map indication	LCD (#1- #8)
Shielded indication	LCD (#9)
Low battery display	LCD (6.5V)
Battery type	DC9.0V (NEDA 1604/6F22 DC9V) x1pc
Dimension(LxWxD)	185 x 80 x 32mm

### QNF-868A Remote unit specifications

Compatible with connectors	RJ11,RJ45,BNC,USB
Dimension(LxWxD)	107 x 30 x 24mm